



1 Best protection against electromagnetic interference is achieved by connection of the cable screens to PE.  
 For special cases with longer cables and small differences in earth potential between RHM and RHE installation the screens can be connected to PE\_C. In case of substantial potential differences a potential equalization cable is mandatory.

**!** When connecting the sensor and transmitter the respective local code for electrical installations must be considered.  
 Beware that there might be additional considerations for installation in hazardous areas.

**!** Do not open the RHE42 under power.

*Terminal assignment channel 2, drawing shows I/O option i2*

Version	CH2+	CH2-
	Terminal	Terminal
i1	42	43
i2	46	47
FF, F2	77	78
PA, P2	77	78

Terminal	Function	Terminal	Function
42	Digital output 2 (+)	43	Digital output 2 (-)
46	Digital input 1 (+)	47	Digital input 1 (-)
77	Foundation Fieldbus FFH1 (FISCO) (+)	78	Foundation Fieldbus FFH1 (FISCO) (-)
77	Profibus PA (FISCO) (+)	78	Profibus PA (FISCO) (-)

**!** NOTE:  
 Intrinsically safe I/O circuits must only be operated with certified barriers or isolating amplifiers

created / revised  
 Date 22.11.2022  
 Drawn H.G.Rudolph  
 Appr. M.Weber



Wiring Diagram RHE42 (is)  
 RHE42-\*\*\*\*\_\*\*P2-\*\*\*\*\_\*\*\*

Project	
Customer	
Draw. - Rev.	E42W-E_P2_Rev_1_2
Sheet	1 / 1